

DC-One



Software V1.2.0 Read Me file

Welcome to software version 1.2.0 for the DC-One Editor Software and firmware. This document contains important information and updates regarding the installation and use of V1.2.0 software.

Contents

1. Important Information for Updating Hardware
2. System Requirements
3. What's New in V1.2.0
4. Installing V1.2.0 Software and Firmware

1. Important Information for Updating Hardware

*****Important*****

For existing users of DC-One hardware and software please use the V1.0 software to back up and store any existing settings or User Presets to your PC. During the process of updating the firmware in the unit to V1.2.0, all existing User Presets and settings are erased. After the update, the stored settings may be transferred to, and stored in, the hardware.

To back up settings to your PC, do the following:

1. **Connect the DC-One hardware to the PC**
2. **Launch the DC-One Editor Software**
3. **When asked in which direction to sync the information, read the data into the PC.**
4. **Click File->Save As and select a location on your hard disc to save the files to.**
5. **Recall any User Presets as needed and repeat the process.**

After storing your data, you may proceed with the software and firmware update.

2. Minimum System Requirements

The following are the System Requirements for installing and running the Dc-One Editor Software.

- PC* with Pentium IV 1.2 GHz or equivalent processor (1.6 GHz or better is recommended)
- Microsoft Windows XP Service Pack 2 or Vista (32-bit Only)
- Microsoft .Net 2.0 Framework
- 256 MB RAM
- Hard disk with 250 MB of storage available
- VGA Monitor (1024x768)
- Graphics card, High Color (16-bit)
- Mouse
- Keyboard
- One USB port

*PC refers to Personal Computers running the specified Windows Operating Systems. Intel-based Apple computers are only supported when running the specified Windows OS natively under Boot Camp. Virtualization, such as that offered by VMware or Parallels, is not officially supported.

3. What's New in V1.2.0

The following is a list of new features or enhancements that can be found in DC-One Editor V1.2.0

- Graphic EQ Function Available
- Compare/Edit Mode Available in GUI. Edit Mode must be entered in the GUI before editing can be done.
- Master/Slave Mode Available
- Improved front panel locking and security
- Improved Preset locking and security
- Improved Preset name storage behavior
- USB port lockable from front panel
- When in Full Edit Mode, input DSP sections can be linked or unlinked independent of the current DSP Configuration. Current Link status is displayed in the DSP window.
- Improved Total Delay Time display in Output Delay Window
- Fixed parameter display bug in Overview Window
- Fixed minor display bugs
- New Tour X Speaker Settings for:
 - TX1122-1181 2W
 - TX1152-1181 2W
 - TX1152 X2-2181 2W
 - TX152-2181 2W
- New Phoenix Speaker Settings for:
 - PX2122 2W v2-0
 - PX2122 X1_PX2181 3W v2-0
 - PX2122 X2_PX2181 3W v2-0
 - PX2152 2W v2-0
 - PX2152 X1_PX2181 3W v2-0
 - PX2152 X2_PX2181 3W v2-0

4. Installing V1.2.0 Software and Firmware

Download the Software

Go to the Electrovoice web site to download software.

<http://www.electrovoice.com/products/530.html>

About Microsoft .Net 2.0 Framework

The .NET Framework is Microsoft's comprehensive programming model for building applications that have visually stunning user experiences with seamless and secure communication.

It is necessary to have .NET Framework installed on your computer. Check for

.NET Framework on your computer by going to Start/Control Panel/Add-Remove Programs. From the Install list, look for Microsoft .NET Framework

2.0. - or visit <http://www.microsoft.com> and search for Microsoft .NET Framework 2.0.

Install DC-One Software

1. After downloading the DC-One software, extract the setup files from the zip file.
2. Double click on the Setup DC-One.msi

*****Important*****

The DC-One Hardware must not be connected during installation

3. Windows Installer Package and follow the instructions.
4. After the Windows Installer Package has been installed, double click on the Setup.exe file and follow the instructions.

Updating DC-One Firmware

1. Connect the DC-One hardware to the USB port on the PC
2. If this is the first time the DC-One hardware has been connected to the PC, the New Hardware Wizard will launch.

3. Allow the New Hardware Wizard to automatically install the driver by clicking Next to advance through the Wizard Menus.
4. After the Driver has been properly installed, launch the DC-One Editor Software
5. The software will prompt you to update the firmware. Click OK and the firmware will automatically update

DC-One



For additional warranty repair or service information, contact the appropriate Telex service department listed below:

Telex Communications Inc.

USA, Canada & Latin America

EV/Dynacord Speakers and Electronics Sales & Technical Support

12000 Portland Ave South,

Burnsville, MN 55337, USA

USA:

Phone: 1-800-392-3497

Fax: 1-800-955-6831

Canada:

Tel: 1-866-505-5551

Fax: 1-866-336-8467

Latin America:

Tel: 1-952-887-5532

Fax: 1-952-736-4212

USA, Canada & Latin America

(EV/Dynacord Speakers and Electronics Service)

Telex Communications, Inc. (Attention: Service)

1 Telex Drive

Morrilton, AR 72110 USA

Tel: 1-800-685-2606, ext. 5265

Fax: 501/354-1118

United Kingdom

Telex Communications Ltd.

4, The Willows Centre

Willow Lane, Mitcham, Surrey CR4 4NX,

United Kingdom

Tel: +44 208 646 7114

Fax: +44 208 640 7583

Japan & Korea

EVI Audio Japan Ltd.

5-3-8 Funabashi, Setagaya-Ku,

Tokyo, Japan 156-0055

Tel: +81 3-5316-5020

Fax: +81 3-5316-5031

Australia & New Zealand

(Independent Distributor)

APAC Audio Pty Ltd.

James Ruse Business Park

Unit 2C, 6 Boundary Road

Northmead, NSW 2152 Australia

Tel: +61 612-9683-4752

Fax: +61 612-9890-5928

Germany, Rest of Europe and

Africa & Middle East

Telex EVI Audio GmbH.

Hirschberger Ring 45

D 94315, Straubing, Germany

Tel: +49 9421-706 0

Fax: +49 9421-706 265

Hong Kong & China

Telex EVI Audio (Shanghai) Co. Ltd.

Room 2214-2215, Tower B, Far East

International Plaza, No. 317 Xianxia Road

Changning District, Shanghai 200051

Tel: +86 21-6235-1677

Fax: +86 21-6235-1676

France

EVI Audio France S.A.

Parc de Courcerin, Allée Lech Walesa,

F 77185 Lognes, France

Tel: +33 1-6480-0090

Fax: +33 1-6006-5103

Singapore & South East Asia

Telex Pte. Ltd.

3015A Ubi Road 1

05-10 Kampong Ubi Industrial Estate

Singapore 408705

Tel: +65 6746 8760

Fax: +65 6746 1206

