



TXS-631SET

Order No.: 25.3660

EUR 229,00

RRP *

PRODUCTINFOS

Multifrequency microphone system,

with UHF PLL technology.

- 1 pocket transmitter, 1 tie clip microphone, 1 receiver, 1 plug-in power supply
- True diversity system
- 80 selectable UHF channels (863-865 MHz)
- ACT function for transmitting the selected frequency to the pocket transmitter via infrared signal
- Autoscan
- Volume and squelch controls
- Gain can be adjusted at the pocket transmitter
- Indication for channel, antenna A/B, ACT status and AF audio level (receiver), channel and battery status (pocket transmitter)
- Robust metal housing (receiver)

Licence-free in the EU.

TECHNICAL SPECIFICATIONS

TXS-631SET

General information	-
Type	multifrequency microphone system
Carrier frequency range	863-865MHz
Audio frequency range	50-18000Hz
Channels	1
THD	<0,5%
Dynamic range	120dB
RF S/N ratio	105dB
Operating time	-
Admiss. ambient temp.	0-40°C
Power supply	-
Dimensions	-
Total weight	-
Connections	-
Specifications transmitter	-
Transmitting power	<10mW
Operating range	≈30m
Power supply transmitter	2 x 1.5 V batt. AA size
Width transmitter	62mm
Height transmitter	105mm
Depth transmitter	25mm
Weight transmitter	88g
Connections transmitter	-
Specifications receiver	-
Audio signal receiver	350 mV/10 kΩ (jack)25 mV/10 kΩ (XLR, bal.)
Power supply receiver	via encl. plug-in power supply
Width receiver	152mm
Height receiver	38mm
Depth receiver	120mm
Weight receiver	482g
Connections receiver	1 x 6.3 mm jack, unbal.1 x XLR, bal.

* **Important Notice:** The retail prices shown here are non-binding recommendations that retailers can charge their customers. They are not part of any specific offer or advertisement. These prices include all charges as well as VAT, but do not cover any additional delivery and shipping costs. Our latest price lists for the retail market include all applicable delivery and payment terms for retailers.